

GoldSMS Blast Config

GoldSMS Blast Configuration (v. 1.10.035)

GoldSMS Blast

Outbound Configuration

Default User ID:

Cell Phone Field:

☒ Notify Admin if Disconnect

Admin Email:

SMTP:

Port:

SMTP User:

SMTP Password:

Prob. Report Phone #:

ID Code:

Polling interval, seconds:

GoldMine Startup Locations and Credentials

GoldMine Path:

GM User: GM PW:

Resilience Mode: Confirm:

GoldMine: GoldMine:

Contact Alias:

Test/Load

OK Cancel

We'll draw your attention to a few of the less-obvious features of GoldSMS Blast.

You must specify a single specific field in which GoldSMS Blast will find the contact's cell number. One implication of this is that GoldSMS Blast cannot, at present, be used to Text "additional" contacts.

The problem report phone number is the number your recipients will be instructed to call should they have any questions, or wish to complain, or ask that they not receive further texts.

From:
<http://plain-english.com/goldsmsdoc/> - **GoldSMS User and Admin Guide**

Permanent link:
http://plain-english.com/goldsmsdoc/doku.php?id=goldsms_blast_config&rev=1392637837

Last update: **2014/02/17 06:50**

