Components of GoldSMS

GoldSMS Pull Config

GoldSMS Inbound Text Configuration (v. 1.10.03	5)
GoldSMS Inbound Configuration	
Cloud Server Connection	
Server Address: goldsms.plain-english.com	Test Connection
User Name: goldsms	
Password:	
Database Name: 9333866	Polling interval, seconds: 10
Assigned TXT Number*: 2487427196	
- Contact Match	GoldMine Startup Locations and Credentials
C1 Match Field(s): phone1,phone2,phone3	GoldMine Path:
C2 Match Field(s): uphonecell	C:\Program Files\GoldMine\gmw.exe
User Match	GM User: GOLDSMS GM PW:
Default User ID: GOLDSMS	Resilience Mode: Confirm:
User ID Match Field:	Jump Start Test/Load
✓ Include inbound "voice" hits	GoldMine Alias: Main PE GoldMine
✓ Set GoldMine Alarm on Retrieval	Contact Alias: Main PE GoldMine
Record Type: Other,0	Administrator Alert
₩rite inbound messages to log file	Admin Email: steveng@plain-english.com
	SMTP: task.plain-english.cc
	Test Port: 26
	SMTP User: pedomain\steven
	SMTP Password: Soccessore
ОК	Cancel

We'll draw your attention to a few of the less-obvious features of GoldSMS Pull.

- The "Assigned Text Number" is your new "corporate" text number, provisioned for you by Plain English.
- Contact Match: GoldSMS Pull will try to identify the contact to link an inbound message to based on the inbound's cell number matching a phone number in one of the GoldMine fields you designate.
 Note: You will have problems if duplicates exist! The inbound message will be linked only to the first match found.
- Unmatched messages get linked to a contact with company name = GoldSMS Catchall. You should create this record!
- GoldSMS Pull matches the User ID by trying to determine which GoldMine user might have sent the Text that is now being replied to. However, you can instruct GoldMine to always link to a specific user for specific records, by designating a User Match field.
- If the Resilience Mode is set to one of the Jump Start options, GoldSMS Blast will try to actively re-start GoldMine (in DDE or GoldSync silent mode) and, so, will need the appropriate login information.
- If Resilience Mode is set to Continue, GoldSMS Blast will simply keep trying to poll the database.
- If Resilience Mode is set to Exit, GoldSMS Blast will simply shut down.

1/2

From: http://plain-english.com/goldsmsdoc/ - GoldSMS User and Admin Guide

Permanent link: http://plain-english.com/goldsmsdoc/doku.php?id=goldsms_pull_config&rev=1392644150



Last update: 2014/02/17 08:35